

BRUKSANVISNING INSTRUCTION MANUAL NAMRON METIS 260 DIM








namron

220-240V~ 50/60Hz IP20

IP20   

Effekt:	12W	Power:	12W
Spenning:	200-240V AC 50Hz	Input voltage:	200-240V AC 50Hz
Lysutbytte:	1207/1247/1213lm	Light output:	1207/1247/1213lm
Fargetemperatur:	3000/4000/5700K	Color temperature:	3000/4000/5700K
CRI:	>80	CRI:	>80
Kapslingsgrad:	IP20	Ingress protection:	IP20
Slagfasthet:	IK08	Impact resistance:	IK08
Driftstemperatur:	-20 – 45°C	Operating temperature:	-20 – 45°C
Materiale:	Polykarbonat	Material:	Polycarbonate
Dimbar:	Ja	Dimmable:	Yes
Levetid:	50.000t	Lifetime:	50,000h

MONTERING/MOUNTING

1  <p>Take out ceiling light and accessory pack from box.</p>	2  <p>Take the lamp cover apart by rotating it in anti-clockwise direction.</p>	3  <p>Knock-in the plastic anchor into ceiling.</p>	4  <p>Put the L.N wire through the lamp base, fix the lamp base by screw.</p>
5  <p>If with 3CCT function, choose preferred color by slide switch.</p>	6  <p>Rotate the lamp cover clockwise until it fix tightly with the base.</p>	7  <p>Switch on.</p>	

TIL INFORMASJON

1. Skal installeres av autorisert el-installatør.

ADVARSEL

1. Produsenten vil ikke holdes ansvarlig for feil installasjon, gal eller upassende bruk og uautorisert forandring av armaturen. Feil som oppstår på grunn av ovennevnte advarsler kan resultere i alvorlige skader på personer, dyr eller gjenstander.
2. Hvis forandringer på produktet er nødvendig, konsultere forhandler for råd.
3. Dersom skader på armaturen oppstår, vennligst erstatt med originaldeler før bruk.
Lyskilden til denne armaturen er ikke utskiftbar. Når lyskilden slutter å virke, må hele armaturen skiftes ut.

FOR INFORMATION

1. Installation must be performed by a qualified electrician.

WARNING

1. The manufacture will not be held responsible for improper installation, faulty or improper use and unauthorized alteration of the luminaire. Errors that occur because of the above warnings can result in serious injury to persons, animals or objects. If changes of the product is required, consult the dealer for advice.
2. If damage of the luminaire occurs, please replace with the original parts before use.
3. The light source of this luminaire is not replaceable; when the light source reaches its end of life, the whole luminaire shall be replaced.